

# DCP-L2520D

Mono Laser Multi-Function Centre

**brother**  
at your side

# Sturdy & Durable.

## Laser Multi-Function for Office.



**2,600-page**  
standard yield  
toner  
included

### DCP-L2520D

Print | Scan | Copy



30ppm  
High Print Speed



Automatic  
2-sided Printing  
(A4 only)



250-sheet  
Paper Tray

# DCP-L2520D

## Mono Laser Multi-Function Centre

**brother**  
at your side

| General                                |  |
|--|--|
| Memory                                 | 32MB   |
| Interface                              | Hi-Speed USB 2.0   |
| Control Panel                          | 16 characters x 2 lines LCD  |
| Toner Save Mode                        | Save toner by printing documents in toner save mode  |
| Monthly Dutycycle                      | 10,000 pages   |
| Print Function                         |  |
| Print Speed A4                         | Up to 30ppm  |
| 2-Sided Print                          | Yes (A4 only)  |
| Print Resolution                       | 600 x 600 dpi, HQ1200 (2400 x 600 dpi) quality   |
| First Print Out Time (From ready mode) | <8.5 secs  |
| Warm-up time (From sleep mode)         | <9 secs  |
| Copy Function                          |  |
| Copy Speed                             | Up to 30cpm  |
| Copy Resolution                        | 600 x 600 dpi  |
| First copy out time                    | <10 secs   |
| Multi-Copy                             | Yes (Up to 99)   |
| N-in-1 Copying                         | Allows the user to compress 2 or 4 pages onto a single A4 sheet                              |
| Scan Function                          |  |
| Scan Resolution                        | Scanner glass: Up to 600 x 2,400 dpi<br>Enhanced: Up to 19,200 x 19,200 dpi                  |
| 2-Sided Scan                           | Manual   |
| Scan Functions                         | Enables users to scan documents to E-mail, Image, OCR , File and Sharepoint (PC only)        |
| Media Specifications                   |  |
| Media Types                            | Standard paper tray - Plain paper, Thin Paper, Recycled Paper                                |
| Media Capacity                         | 250-sheet standard paper tray<br>1-sheet manual feed slot                                    |
| Media Sizes                            | Standard tray - A4, Letter, A5, A5(Long Edge), A6, Executive, Legal, Folio                   |
| Paper Output                           | 100-sheet  |
| Support Operating System               |  |
| Windows                                | Windows 8.1/ 8/ 7, Windows Vista, Windows XP Home/<br>Professional/ Professional x64 Edition |
| Macintosh                              | Mac OS X v10.7.5, 10.8.x, 10.9.x (Download only)   |
| Linux***                               | CUPS, LPD/LPRng (x86/x64 environment)  |
| Dimensions (WxDxH)                     |  |
| With Carton                            | 567 x 517 x 414mm / 12.7kg   |
| Without Carton                         | 409 x 398.5 x 267mm / 9.7kg  |
| Supplies                               |  |
| Inbox Toners                           | 2,600 pages*   |
| High Yield Toners                      | TN-2365 2,600 pages*   |
| Other Supplies                         | Drum (DR-2365) Up to 12,000 pages^   |
| Environment                            |  |
| Power Consumption                      | Ready: 60W, Printing: 510W, Sleep: 6.6W, Deep Sleep: 1.1W                                    |
| Noise Level                            | 50dBA (Printing), 33dBA (Ready), 45dBA (Quiet)   |

\* Declared yield value in accordance with ISO/IEC 19752 \*\* (ITU-T Test Chart, Standard Resolution, MMR) \*\*\* Optional free download available from <http://solutions.brother.com>. ^Drum yield may vary by type of use.

India EPR Compliance | Entity Name: Brother International (India) Private Limited  
Plastic Waste EPR No.: BO-13-000-08-AAOCB0263E-22 | Battery Waste EPR No.: 6821475  
Thickness for PE bag: 50 microns or above



Brother strongly recommends the use of genuine Brother consumable products only. Benefits include better quality print, greater yield per consumable, protection of your machine from damage and achievement of optimum performance. As a precaution, please note that your machine warranty may not cover any damage arising from the use of non-genuine consumables.

**brother**

**Brother International (India) Pvt. Ltd.**  
Toll Free : 1800 222 422 (For MTNL & BSNL user), 1800 209 8904 (For Others)  
Operating Hours: Mon. to Fri. (8.30am to 6.30pm) & Sat. (9.00am to 6.00pm)  
Closed on Sunday and Public Holidays.

[www.brother.in](http://www.brother.in)