

HL-L2400D

Mono Laser Printer

brother
at your side

AFFORDABLE **LASER PRINTER** FOR HOME & OFFICE



**30 Pages
Per Minute**



**Auto Duplex
Printing**



**250 Sheets
Paper Tray**



**3,000 Pages
Inbox Toner**



**Print
Only**

HL-L2400D

Key Function		Print Only
Print Speed (A4/Letter)		Up to 30/32 ppm
Print Resolution		Up to 1,200 x 1,200 dpi
First Print Out Time (Ready)		Less than 8.5 secs
2-sided Feature (A4/Letter Auto Duplex Print)		Yes
Connectivity/Networking		
Interface		Hi-Speed 2.0
Paper Handling		
Input Tray (Standard)		250 Sheets
Manual Slot		1 Sheet
Output Tray (Face Down)		150 Sheets
Media Weights		60 to 230g/m ² (Using Manual Feed Slot)
Media Size		A4, Letter, B5 (JIS), B5 (ISO), A5, A5 (Long Edge), B6 (JIS), A6, Executive, Legal*, A4 Short, Folio*, Mexico Legal*, India Legal
Others		
Processor Speed		600MHz
Memory		64MB
Duty Cycle		Max. monthly print Vol. up to 35,000 pages
Display		LED
OS Compatibility		Windows 10, 11 Linux: CUPS, LPD/LPRng (x86/x64 environment)
Utilities & Solutions		BRAdmin Pro4: Windows (by Download)
Power Consumption (Printing/Printing with Quiet mode)		Approx. 440W/270W
Power Source		220-240V AC 50/60Hz
Noise Level (Printing/Printing with Quiet mode) ⁱⁱ		LpAm = 48 dB(A)/44 dB(A)
Supplies		
Standard-Yield Toner ^{iii & v}		TN2570XL / 3,000 pages
High-Yield Toner ⁱⁱⁱ		TN2570XXL / 5,000 pages
Drum		DR2570 / 15,000 pages
Dimension and Weight		
Dimension (W x D x H)		356 x 360 x 183 mm
Weight		7.1kg

ⁱ In accordance with ISO/IEC17991

ⁱⁱ In accordance with ISO7779

ⁱⁱⁱ In accordance with ISO/IEC19752

^{iv} Information correct as at the time of publication and may change without prior notice.

^v Inbox toner

^{vi} India EPR Compliance | Entity Name: Brother International (India) Private Limited

Plastic Waste EPR No.: BO-13-000-08-AADCBO263E-22 | Battery Waste EPR No.: 6821475 | Thickness for PE bag: 50 microns or above



Working with you for a sustainable future.
www.brotherearth.com



One-stop centre for free downloadable templates



Brother strongly recommends the use of genuine Brother consumable products only. Benefits include better quality print, greater yields per consumable, protection of your machine from damages and achievement of optimum performance. As a precaution, please note that your machine warranty may not cover any damages arising from the use of non-genuine consumables.

Brother International (India) Private Limited



☎ • 1-800-222-422 • 1-800-209-8904 (Toll Free)
✉ • customercare@brother.in | 🌐 • www.brother.in

Operating Hours:

📅 Monday - Friday | Saturday
🕒 8:30 AM - 6:30 PM | 9:00 AM - 6:00 PM
🚫 Closed on Sunday & Public Holidays



SCAN TO CHAT

7045 450 450

