Mono Laser Printer



PROFESSIONAL LASER PRINTER WITH IMPRESSIVE SPEED











34 Pages Per Minute

Auto Duplex Printing

250 Sheets Paper Tray

3,000 Pages Inbox Toner









www.brother.in


	HL-L2460DW
Key Function	Print Only
Print Speed (A4/Letter)	Up to 34/36ppm
Print Resolution	Up to 1,200 x 1,200 dpi
First Print Out Time (Ready)	Less than 8.5 secs
2-sided Feature (A4/Letter Auto Duplex Print)	Yes
Connectivity/Networking	
Interface	Hi-Speed 2.0, Ethernet (10 Base-T/100 Base-TX), Wi-Fi Direct,
	Dual Band Wireless LAN (2.4GHz/5.0GHz)
Mobile Solutions	AirPrint, Mopria, Mobile Connect
Paper Handling	
Input Tray (Standard)	250 Sheets
Manual Slot	1 Sheet
Output Tray (Face Down)	150 Sheets
Media Weights	60 to 230g/m² (Using Manual Feed Slot)
Media Size	A4, Letter, B5 (JIS), B5 (ISO), A5, A5 (Long Edge), B6 (JIS), A6, Executive, Legal*,
	A4 Short, Folio*, Mexico Legal*, India Legal
Others	
Processor Speed	600MHz
Memory	128MB
Duty Cycle	Max. monthly print Vol. up to 35,000 pages
Emulation	PCL6
Display	1 Line LCD (16 characters)
OS Compatibility	Windows 10, 11, Server 2012 (Network only), Server 2012 R2 (Network only), Server 2016 (Network only), Server 2019 (Network only), Server 2022 (Network only) Linux: CUPS, LPD/LPRng (x86/x64 environment)
Utilities & Solutions	BRAdmin Light: Windows (by Download), BRAdmin Pro4: Windows (by Download)
Security Features	Setting Lock, Network Security
Power Consumption (Printing/Printing with Quiet mode)	Approx. 470W/270W
Power Source	220-240V AC 50/60Hz
Noise Level (Printing/Printing with Quiet mode)	LpAm = 49 dB(A)/44 dB(A)
Supplies	
Standard-Yield Toner ^{™&v}	TN2570XL / 3,000 pages
High-Yield Toner ⁱⁱⁱ	TN2570XXL / 5,000 pages
Drum	DR2570 / 15,000 pages
Dimension and Weight	
Dimension (W x D x H)	356 x 360 x 183 mm
Weight	7.1kg

In accordance with ISO/IEC17991 In accordance with ISO7779

Inidia EPR Compliance | Entity Name: Brother International (India) Private Limited
Plastic Waste EPR No.: BO-13-000-08-AADCB0263E-22 | Battery Waste EPR No.: 6821475 | Thickness for PE bag: 50 microns or above











Brother strongly recommends the use of genuine Brother consumable products only. Benefits include better quality print, greater yields per consumable, protection of your machine from damages and achievement of optimum performance. As a precaution, please note that your machine warranty may not cover any damages arising from the use of non-genuine consumables.

Brother International (India) Private Limited









Sign Am - 6:30 PM | 9:00 AM - 6:00 PM Closed on Sunday & Public Holidays





<sup>Information correct as at the time of publication and may change without prior notice.

■ Information correct as at the time of publication and may change without prior notice.

■ Information correct as at the time of publication and may change without prior notice.

■ Information correct as at the time of publication and may change without prior notice.

■ Information correct as at the time of publication and may change without prior notice.

■ Information correct as at the time of publication and may change without prior notice.

■ Information correct as at the time of publication and may change without prior notice.

■ Information correct as a set the time of publication and may change without prior notice.

■ Information correct as a set the time of publication and may change without prior notice.

■ Information correct as a set the time of publication and may change without prior notice.

■ Information correct as a set the time of publication and may change without prior notice.

■ Information correct as a set the time of publication and the time of the time</sup>

Inbox toner